



RF-D10EG DAB / DAB + compatible radio

| | | | |
|-----------------|-------------------------------|--------------------------------------|--|
| TUNER | | Band / programs | FM 87.5-108.0 MHz (step 50 KHz) / DAB BANDIII (5A-13F) |
| | | DAB | DAB / DAB + |
| | | FM | Yup |
| | | RDS | Yup |
| | | Stylus antenna (for FM / DAB) | 67cm |
| AUDIO SYSTEM | Channel exit | | 1 channel |
| | Output power (RMS) | Total power | 2 W (10% THD) |
| Speaker system | | Configuration | 1 1-way speaker |
| | | Speaker unit | Full range: 10 cm (4 ohm) |
| Easy to use | | 10-channel memory | Yup |
| | | 5 predefined EQs | Yes (flat / heavy / clear / soft / voice) |
| | | DAB Scanning * 1 | Yup |
| | | Automatic tuning | Yes (for FM) |
| | | Programmable timer | PLAY / SLEEP |
| | | Battery level indicator | Yup |
| | | Clock (automatic time adjustment) | Yup |
| DESIGN | Easy on- screen display | Screen format (display area) | Large display 74 x 21 mm |
| | | LCD | Yes (with white backlight) |
| | | Figure | Digits + 2 x 16 icons |
| | 10 direct selection keys | | Yup |
| | | | |

| | | |
|---|---|---|
| | Folding handle | Yup |
| Inputs and outputs | Headset / headset (3.5 mm) | Yes (Mini stereo) |
| ACCESSORIES INCLUDED | AC power cord | Yup |
| Supply | B.C | 230 V, 50 Hz |
| | Battery | DC 6 V / C x 4 (R14 / LR14) |
| Consumption | Normal use [around] | 7 W |
| | Standby [around] | 0.6 W |
| Battery life in use * 2 - R14 manganese / LR14 alkaline | DAB [around] | 12 h / 40 h |
| | FM [around] | 9 h / 30 h |
| Size, weight | Dimensions (L x H x D) [approximately] | 251 x 138 x 91 mm |
| | Weight (with batteries) [approximately] | 1.3 kg |
| | Weight (without batteries) [around] | 1 kg |
| Note | | * 1 For DAB scanning select "Full Scan" from the MENU. * 2 Use Panasonic batteries. Specifications are subject to change without notice. Weight and dimensions are approximate. |